

Load Balancing Microsoft Print Server

Version 1.3.2



Table of Contents

1. About this Guide	3
2. Loadbalancer.org Appliances Supported	3
3. Software Versions Supported	3
3.1. Loadbalancer.org Appliance	3
3.2. Microsoft Windows Server	3
4. Related Documentation	3
5. Load Balanced Ports / Services.	3
6. Appliance Configuration Overview	3
6.1. Operation Mode	3
6.2. Print Server Health-check	4
6.3. Deployment Concept	4
7. Deploying & Accessing the Appliance	4
7.1. Deployment	4
7.2. Accessing the Appliance WebUI	4
Main Menu Options	6
8. Configuration Steps	6
8.1. Appliance Configuration	6
Configure the Virtual Service (VIP)	6
Define the Real Servers	7
8.2. Print Server Configuration	7
Solve the ARP Problem	7
Enable Microsoft Print Server Load Balancing	13
9. Testing & Verification	15
10. Deploying Load Balanced Printers via Group Policy	16
11. Loadbalancer.org Technical Support	16
12 Document Revision History	17

1. About this Guide

This document provides a quick reference guide on how to load balance Microsoft Print Servers using Loadbalancer.org appliances.

2. Loadbalancer.org Appliances Supported

All our products can be used with Microsoft Print Server. For full specifications of available models please refer to https://www.loadbalancer.org/products.

Some features may not be supported in all cloud platforms due to platform specific limitations, please check with Loadbalancer.org support for further details.

3. Software Versions Supported

3.1. Loadbalancer.org Appliance

v8.3.8 and later

8 Note

The screenshots used throughout this document aim to track the latest Loadbalancer.org software version. If using an older software version, note that the screenshots presented here may not match the WebUI exactly.

3.2. Microsoft Windows Server

Windows Server 2012 and later

4. Related Documentation

For additional information, please refer to the Administration Manual and the relevant Quick Start / Configuration Guide.

5. Load Balanced Ports / Services

Ports	Uses	Transport Layer Protocol
445	SMB	TCP
515	LPD	TCP

6. Appliance Configuration Overview

6.1. Operation Mode


The load balancer is configured using layer 4 DR mode. This mode requires the "ARP Problem" to be solved on each Real Server. For more information, please refer to Solve the ARP Problem.

6.2. Print Server Health-check

A connect to port health-check on port 445 is used to verify that each Print Server is available.

6.3. Deployment Concept

Once the load balancer is deployed, clients connect to the Virtual Service (VIP) on the load balancer rather than directly to one of the Print Servers.



7. Deploying & Accessing the Appliance

7.1. Deployment

Deploy the Loadbalancer.org appliance as described in the relevant Quick Start / Configuration Guide.

7.2. Accessing the Appliance WebUI

The WebUI is accessed using a web browser. By default, users are authenticated using Apache authentication. Users can also be authenticated against LDAP, LDAPS, Active Directory or Radius - for more information, please refer to External Authentication.

8 Note	There are certain differences when accessing the WebUI for the cloud appliances. For details, please refer to the relevant Quick Start / Configuration Guide.
8 Note	A number of compatibility issues have been found with various versions of Microsoft Internet Explorer and Edge. The WebUI has been tested and verified using both Chrome & Firefox.

1. Using a browser, navigate to the following URL:

https://<IP-address-configured-during-the-network-setup-wizard>:9443/lbadmin/

8 Note

You'll receive a warning about the WebUl's certificate. This is due to the default self signed certificate that is used. If preferred, you can upload your own certificate - for more information, please refer to Appliance Security Features.

2. Log in to the WebUI using the following credentials:


Username: loadbalancer

Password: <configured-during-network-setup-wizard>

8 Note

To change the password, use the WebUI menu option: *Maintenance > Passwords*.

Once logged in, the WebUI will be displayed as shown below:



3. You'll be asked if you want to run the Setup Wizard. Click **Dismiss** if you're following a guide or want to configure the appliance manually. Click **Accept** to start the Setup Wizard.

Note The Setup Wizard can only be used to configure Layer 7 services.

Main Menu Options

System Overview - Displays a graphical summary of all VIPs, RIPs and key appliance statistics

Local Configuration - Configure local host settings such as IP address, DNS, system time etc.

Cluster Configuration - Configure load balanced services such as VIPs & RIPs

Maintenance - Perform maintenance tasks such as service restarts and taking backups

View Configuration - Display the saved appliance configuration settings

Reports - View various appliance reports & graphs

Logs - View various appliance logs

Support - Create a support download, contact the support team & access useful links


Live Chat - Start a live chat session with one of our Support Engineers

8. Configuration Steps

8.1. Appliance Configuration

Configure the Virtual Service (VIP)

- 1. Using the WebUI, navigate to: *Cluster Configuration > Layer 4 Virtual Services* and click **Add a New Virtual Service**.
- 2. Enter the following details:



- Define the required *Label* (name) for the VIP, e.g. **PrintServer**.
- Set the Virtual Service IP address field to the required IP address, e.g. 192.168.100.10.
- Set the Virtual Service Ports field to 445,515.




- Leave the *Protocol* set to **TCP**.
- Leave the Forwarding Method set to Direct Routing.
- 3. Click Update.
- 4. Now click **Modify** next to the newly created Virtual Service.
 - Scroll to the *Heath Checks* section.
 - Ensure the *Health Check* is set to **Connect to Port**.
 - Click [Advanced] and set the Check Port to 445.
- 5. Click Update.

Define the Real Servers

The Real Servers (i.e. the Print Servers) must now be associated with the VIP.

- 1. Using the WebUI, navigate to: *Cluster Configuration > Layer 4 Real Servers* and click **Add a new Real Server** next to the newly created VIP.
- 2. Enter the following details:



- Enter an appropriate label for the Real Server, e.g. PS1.
- Change the Real Server IP Address field to the required address, e.g. 192.168.100.20.
- 3. Click Update.
- 4. Repeat the above steps to add your other Print Server(s).

8.2. Print Server Configuration

Solve the ARP Problem

Layer 4 DR (Direct Routing) mode works by changing the MAC address of inbound packets to match the Real Server selected by the load balancing algorithm. Steps must taken for each Real Server to enable DR mode to work correctly. This is known as "solving the ARP Problem". The exact steps required depend on the particular operating system in use.

8 Note

For more details on the ARP problem, please refer to DR Mode Considerations.

Windows Server 2012 & Later


Windows Server 2012 and later support Direct Routing (DR) mode through the use of the Microsoft Loopback Adapter that must be installed and configured on each load balanced (Real) Server. The IP address configured on the Loopback Adapter must be the same as the Virtual Service (VIP) address. This enables the server to receive packets that have their destination set as the VIP address. If a Real Server is included in multiple DR mode VIPs, an IP address for each VIP must be added to the Loopback Adapter.

In addition, steps must be taken to set the strong/weak host behavior on each Real Server. This is used to either prevent or allow interfaces to receive packets destined for a different interface on the same server.

(1) Important The following 3 steps must be completed on all Real Servers associated with the VIP.

Step 1 of 3: Install the Microsoft Loopback Adapter

- 1. Click **Start**, then run **hdwwiz** to start the Hardware Installation Wizard.
- 2. Once the Wizard has started, click Next.
- 3. Select Install the hardware that I manually select from a list (Advanced), click Next.
- 4. Select Network adapters, click Next.



- 5. Select Microsoft & Microsoft KM-Test Loopback Adapter, click Next.
- 6. Click **Next** to start the installation, when complete click **Finish**.

Step 2 of 3: Configure the Loopback Adapter

- 1. Open Control Panel and click Network and Sharing Center.
- 2. Click Change adapter settings.




3. Right-click the new Loopback Adapter and select Properties.

Note
You can configure IPv4 or IPv6 addresses or both depending on your requirements.


when configuring the loopback adapter properties, make sure that Client for Microsoft Networks and File & Printer Sharing for Microsoft Networks is also checked as shown below.

IPv4 Addresses

1. Uncheck all items except Client for Microsoft Networks, File & Printer Sharing for Microsoft Networks and Internet Protocol Version 4 (TCP/IPv4) as shown below:



2. Ensure that Internet Protocol Version (TCP/IPv4) is selected, click Properties and configure the IP address to be the same as the Virtual Service address (VIP) with a subnet mask of 255.255.255.255, e.g. 192.168.2.20/255.255.255.255 as shown below:




Note 192.168.2.20 is an example, make sure you specify the correct VIP address.

Note
If a Real Server is included in multiple DR mode VIPs, an IP address for each VIP must be added to the Loopback Adapter.


3. Click **OK** then click **Close** to save and apply the new settings.

IPv6 Addresses

1. Uncheck all items except Client for Microsoft Networks, File & Printer Sharing for Microsoft Networks and Internet Protocol Version 6 (TCP/IPv6) as shown below:



2. Ensure that Internet Protocol Version (TCP/IPv6) is selected, click Properties and configure the IP address to be the same as the Virtual Service (VIP) and set the *Subnet Prefix Length* to be the same as your network setting, e.g. 2001:470:1f09:e72::15/64 as shown below:



- Note 2001:470:1f09:e72::15/64 is an example, make sure you specify the correct VIP address.
- Note If a Real Server is included in multiple DR mode VIPs, an IP address for each VIP must be

added to the Loopback Adapter.

3. Click **OK** then click **Close** to save and apply the new settings.

Step 3 of 3: Configure the strong/weak host behavior

The strong/weak host behavior can be configured using either of the following 2 methods:

- Option 1 Using Network Shell (netsh) commands
- Option 2 Using PowerShell cmdlets

The commands in this section assume that the LAN Adapter is named "**net**" and the Loopback Adapter is named "**loopback**" as shown in the example below:



(!) Important

Either adjust the commands to use the names allocated to your LAN and loopback adapters, or rename the adapters before running the commands. Names are case sensitive so make sure that the interface names used in the commands match the adapter names exactly.

Option 1 - Using Network Shell (netsh) Commands

To configure the correct strong/weak host behavior run the following commands:

For IPv4 addresses:

```
netsh interface ipv4 set interface "net" weakhostreceive=enabled
netsh interface ipv4 set interface "loopback" weakhostreceive=enabled
netsh interface ipv4 set interface "loopback" weakhostsend=enabled
```

For IPv6 addresses:

```
netsh interface ipv6 set interface "net" weakhostreceive=enabled
netsh interface ipv6 set interface "loopback" weakhostreceive=enabled
netsh interface ipv6 set interface "loopback" weakhostsend=enabled
netsh interface ipv6 set interface "loopback" dadtransmits=0
```

Option 2 - Using PowerShell Cmdlets

For IPv4 addresses:



Set-NetIpInterface -InterfaceAlias loopback -WeakHostReceive enabled -WeakHostSend enabled -DadTransmits 0 -AddressFamily IPv4

Set-NetIpInterface -InterfaceAlias net -WeakHostReceive enabled -AddressFamily IPv4

For IPv6 Addresses:

 $\label{thm:continuous} Set-NetIpInterface - Interface Alias loopback - WeakHostReceive enabled - WeakHostSend enabled - DadTransmits 0 - AddressFamily IPv6$

Set-NetIpInterface -InterfaceAlias net -WeakHostReceive enabled -AddressFamily IPv6

Enable Microsoft Print Server Load Balancing

Pre-Requisites

- 1. Each Print Server must be joined to the same domain as the client PCs.
- 2. Each Print Server must have the **Print and Document Service** role installed.
- 3. All printers must be installed & shared on each Print Server using exactly the same share names and permissions.

8 Note

A number of issues have been reported when using Type 4 print drivers, so whenever possible we recommend using Type 3 drivers. Type 4 drivers are usually bundled with the operating system or are downloaded from Windows update, whereas Type 3 drivers are typically downloaded from the printer manufacturer's website.

Enable access via Hostname

To enable the load balanced Print Servers to be accessed via an appropriate hostname, complete the following steps:

8 Note

The configuration steps below assume the hostname for the VIP is **printserver-vip**. Change this to suit your requirements.

Windows 2019 & Later

For Windows 2019 & later, host entries must be added to the local hosts file and a single Registry Key must be added:

1. Add the following host entries to the local hosts file on each Print Server:

```
<local IP address> <printserver-vip>
<local IP address> <printserver-vip>.<domain>
```

For example, if you have 2 Print Servers - 192.168.100.20 and 192.168.100.21, the following entries must be



added:

a. on the 192.168.100.20 server:

```
192.168.100.20 printserver-vip
192.168.100.20 printserver-vip.domain.com
```

b. on the 192.168.100.21 server:

```
192.168.100.21 printserver-vip
192.168.100.21 printserver-vip.domain.com
```

2. Add the following Registry Key to each Print Server:

 $\label{thm:currentControlSet\Services\lambda} Key: \ HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\Services\lambda\label{thm:currentControlSet\Services\lambda}.$

Value: OptionalNames
Type: REG_MULTI_SZ
Data: printserver-vip

8 Note

In the example presented here, **printserver-vip** is the name that will be used to access the load balanced print servers via the virtual service (VIP) created on the load balancer. This can be set to be any appropriate name, although whatever name is used, it must be the **same name** that is used for the DNS entry described in the "Configure DNS Name Resolution" section below.

Windows 2012 & 2016

For Windows 2012 & 2016, the following Registry Keys must be added to each Print Server:

Key: HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\Control\Lsa

Value: DisableLoopbackCheck

Type: REG_DWORD

Data: 1

 $\label{thm:controlSet} \textbf{Key: HKEY_LOCAL_MACHINE} \\ \textbf{SYSTEM} \\ \textbf{CurrentControlSet} \\ \textbf{Services} \\ \textbf{lanmanserver} \\ \textbf{parameters} \\ \textbf{manual experimentation} \\ \textbf{man$

Value: DisableStrictNameChecking

Type: REG_DWORD

Data: 1

 ${\tt Key: HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\Services\lanmanserver\parameters}$

Value: OptionalNames
Type: REG_MULTI_SZ
Data: printserver-vip

8 Note

In the example presented here, printserver-vip is the name that will be used to access the load


balanced print servers via the virtual service (VIP) created on the load balancer. This can be set to be any appropriate name, although whatever name is used, it must be the **same name** that is used for the DNS entry described in the "Configure DNS Name Resolution" section below.

Configure DNS Name Resolution

Create a DNS Host (A) record for the hostname used for the Virtual Service that points to the VIP address.
 This must match the value set for the REG_MULTI_SZ OptionalNames registry entry, in this example:
 printserver-vip → 192.168.100.10.

Disable NetBIOS over TCP/IP

1. On each Print Server, disable NetBIOS over TCP/IP on all interfaces:



Server Reboot

To apply the changes, reboot each Print Server.

9. Testing & Verification

You should now be able to access your printers using either the Virtual Service IP address or the share name. In the example presented in this guide, either:

\\192.168.100.10

or



\\printserver-vip

or

\\printserver-vip.domain.com

Any shared printers and shared folders that have been configured on the Print Servers should be visible.

10. Deploying Load Balanced Printers via Group Policy

- 1. Ensure that the name you've used for your load balanced Print Server cluster (e.g. **printserver-vip**) is resolvable by DNS as explained above.
- 2. On one of your Print Servers, open: Administrative Tools > Print Management.
 - Right-click Print Servers and click **Add/Remove Servers**.
 - Specify the name you've used for your load balanced Print Server cluster, e.g. printserver-vip and click OK.
 - Expand the *Print Servers* section then expand the new *printserver-vip* section.
 - Select Printers.
 - Right click the printer you want to deploy and click Deploy with Group Policy.
 - Select the relevant GPO and configure the remaining settings according to your requirements.

11. Loadbalancer.org Technical Support

If you have any questions regarding the appliance or would like assistance designing your deployment, please don't hesitate to contact our support team: support@loadbalancer.org.

12. Document Revision History

Version	Date	Change	Reason for Change	Changed By
1.1.0	4 November 2019	Styling and layout	General styling updates	АН
1.1.1	9 June 2020	New title page	Branding update	АН
		Updated Canadian contact details	Change to Canadian contact details	
1.1.2	25 June 2021	Added Print Server load balancing configuration steps for Windows 2019	The steps listed for other versions of Windows do not work for Windows 2019	RJC
1.2.0	1 September 2022	Converted the document to AsciiDoc Updated links and instructions where necessary	Move to new documentation system Required updates	АН
1.2.1	3 November 2022	Removed configuration sections for Legacy environments Added section covering how to solve the ARP problem for Windows 2012 & Later Added port 515 to the VIP Added the OptionalNames Registry key for Windows 2019 & later	Section no longer needed / updated configuration requirements	RJC
1.2.2	7 November 2022	Added minimum software version sections Various minor tidy ups	Additional information	RJC
1.2.3	5 January 2023	Combined software version information into one section Added one level of section numbering	Housekeeping across all documentation	АН
1.2.4	2 February 2023	Updated screenshots	Branding update	АН
1.2.5	8 March 2023	Improved document structure	Document standardization	RJC
1.3.0	24 March 2023	New document theme Modified diagram colours	Branding update	АН

Version	Date	Change	Reason for Change	Changed By
1.3.1	27 April 2023	Added note to say port 515 can be omitted if only have SMB print queues	Remove unnecessary configuration	RJC
1.3.2	24 August 2023	Added note to say that type 3 printer drivers are recommended	Type 4 drivers can cause issues	RJC



Visit us: www.loadbalancer.org

Phone us: +44 (0)330 380 1064

Phone us: +1 833 274 2566

Email us: info@loadbalancer.org

Follow us: @loadbalancer.org

About Loadbalancer.org

Loadbalancer.org's mission is to ensure that its clients' businesses are never interrupted. The load balancer experts ask the right questions to get to the heart of what matters, bringing a depth of understanding to each deployment. Experience enables Loadbalancer.org engineers to design less complex, unbreakable solutions and to provide exceptional personalized support.

