

Load Balancing Nutanix Object Storage

Version 1.0.0



Table of Contents

1. About this Brief	3
2. Loadbalancer.org Appliances Supported	3
3. Software Versions Supported	3
3.1. Loadbalancer.org Appliance	3
3.2. Nutanix Object Storage	3
4. Nutanix Object Storage	3
5. Load Balancing Nutanix Object Storage	3
5.1. Persistence (aka Server Affinity)	4
5.2. Virtual Service (VIP) Requirements	4
5.3. Port Requirements	4
6. Deployment Concept	4
6.1. Multi-Site Deployments	4
7. Load Balancer Deployment Methods	5
7.1. Layer 7 SNAT Mode	5
8. Loadbalancer.org Appliance – the Basics	6
8.1. Virtual Appliance	
8.2. Initial Network Configuration	6
8.3. Accessing the Appliance WebUI	6
Main Menu Options	8
8.4. Appliance Software Update	9
Determining the Current Software Version	9
Checking for Updates using Online Update	
Using Offline Update	
8.5. Ports Used by the Appliance	
8.6. HA Clustered Pair Configuration	
9. Appliance Configuration for Nutanix Object Storage	
9.1. Configuring VIP 1 - Nutanix-HTTP	
9.2. Defining the Real Servers (RIPs)	
9.3. Configuring VIP 2 - Nutanix-HTTPS.	
9.4. Defining the Real Servers (RIPs)	
9.5. Finalizing the Configuration	
10. Testing & Verification	
10.1. Accessing Nutanix Object Storage	
10.2. Using System Overview.	
11. Technical Support	
12. Further Documentation	15
13. Appendix	
13.1. Configuring HA - Adding a Secondary Appliance	
Non-Replicated Settings	16
Configuring the HA Clustered Pair	
14 Document Revision History	19

1. About this Brief

This brief outlines the steps required to configure a load balanced Nutanix Object Storage environment utilizing Loadbalancer.org appliances. It covers the configuration of the load balancers and also any Nutanix Object Storage configuration changes that are required to enable load balancing.

For more information about initial appliance deployment, network configuration and using the Web User Interface (WebUI), please also refer to the Administration Manual.

2. Loadbalancer.org Appliances Supported

All our products can be used with Nutanix Object Storage. For full specifications of available models please refer to https://www.loadbalancer.org/products.

Some features may not be available or fully supported in all cloud platforms due to platform specific limitations. For more details, please refer to the "Main Differences to our Standard (Non-Cloud) Product" section in the appropriate cloud platform Quick Start Guide or check with Loadbalancer.org support.

3. Software Versions Supported

3.1. Loadbalancer.org Appliance

V8.9.1 and later

8 Note

The screenshots used throughout this document aim to track the latest Loadbalancer.org software version. If you're using an older version, or the very latest, the screenshots presented here may not match your WebUI exactly.

3.2. Nutanix Object Storage

All Versions

4. Nutanix Object Storage

Nutanix Object Storage is a scalable and distributed storage system offered by Nutanix, designed for storing and managing large volumes of unstructured data, such as documents, images, videos, and backups. It uses an object-based storage architecture and provides features like data replication, data tiering, and data protection to ensure the high availability and durability of data. Nutanix Object Storage is commonly used in enterprises and cloud environments to efficiently manage and access vast amounts of unstructured data while maintaining performance and reliability.

5. Load Balancing Nutanix Object Storage

R Note

It's highly recommended that you have a working Nutanix Object Storage environment first before implementing the load balancer.

5.1. Persistence (aka Server Affinity)

Nutanix Object Storage does not require persistence to be enabled on the load balancer.

5.2. Virtual Service (VIP) Requirements


To provide load balancing and HA for Nutanix Object Storage, 2 VIPs are required, one for HTTP traffic and the other for HTTPS traffic.

5.3. Port Requirements

The following table shows the ports that are load balanced:

Port	Protocols	Use
80	НТТР	HTTP Object Store Service
443	TCP	HTTPS Object Store Service

6. Deployment Concept



VIP = Virtual IP Address

8 Note

The load balancer can be deployed as a single unit, although Loadbalancer.org recommends a clustered pair for resilience & high availability. Please refer to the section Configuring HA - Adding a Secondary Appliance in the appendix for more details on configuring a clustered pair.

6.1. Multi-Site Deployments

All loadbalancer.org appliances includes GSLB (Global Server Load Balancing) by default. This can be used to support multi-site Nutanix Object Storage deployments. For more information on GSLB, please refer to Global Server Load Balancing.


7. Load Balancer Deployment Methods

The load balancer can be deployed in 4 fundamental ways: Layer 4 DR mode, Layer 4 NAT mode, Layer 4 SNAT mode, and Layer 7 SNAT mode.

For Nutanix Object Storage, layer 7 SNAT mode is recommended since it's simple to implement and does not require any mode specific changes to the Nutanix Object Storage nodes. This mode is described below and is used for the configurations presented in this guide. For configuring using layer 7 SNAT mode please refer to Section 9, "Appliance Configuration for Nutanix Object Storage".

7.1. Layer 7 SNAT Mode

Layer 7 SNAT mode uses a proxy (HAProxy) at the application layer. Inbound requests are terminated on the load balancer and HAProxy generates a new corresponding request to the chosen Real Server. As a result, Layer 7 is typically not as fast as the Layer 4 methods. Layer 7 is typically chosen when either enhanced options such as SSL termination, cookie based persistence, URL rewriting, header insertion/deletion etc. are required, or when the network topology prohibits the use of the layer 4 methods.



- Because layer 7 SNAT mode is a full proxy, any server in the cluster can be on any accessible subnet including across the Internet or WAN.
- Layer 7 SNAT mode is not transparent by default, i.e. the Real Servers will not see the source IP address of the client, they will see the load balancer's own IP address by default, or any other local appliance IP address if preferred (e.g. the VIP address). This can be configured per layer 7 VIP. If required, the load balancer can be configured to provide the actual client IP address to the Real Servers in 2 ways. Either by inserting a header that contains the client's source IP address, or by modifying the Source Address field of the IP packets and replacing the IP address of the load balancer with the IP address of the client. For more information on these methods please refer to Transparency at Layer 7.
- Layer 7 SNAT mode can be deployed using either a one-arm or two-arm configuration. For two-arm deployments, **eth0** is normally used for the internal network and **eth1** is used for the external network



although this is not mandatory.

- · Requires no mode-specific configuration changes to the load balanced Real Servers.
- Port translation is possible with Layer 7 SNAT mode, e.g. VIP:80 → RIP:8080 is supported.
- You should not use the same RIP:PORT combination for layer 7 SNAT mode VIPs and layer 4 SNAT mode VIPs because the required firewall rules conflict.

8. Loadbalancer.org Appliance – the Basics

8.1. Virtual Appliance

A fully featured, fully supported 30 day trial is available if you are conducting a PoC (Proof of Concept) deployment. The VA is currently available for VMware, Virtual Box, Hyper-V, KVM, XEN and Nutanix AHV and has been optimized for each Hypervisor. By default, the VA is allocated 2 vCPUs, 4GB of RAM and has a 20GB virtual disk. The Virtual Appliance can be downloaded here.

8 Note	The same download is used for the licensed product, the only difference is that a license key file (supplied by our sales team when the product is purchased) must be applied using the appliance's WebUI.
8 Note	Please refer to Virtual Appliance Installation and the ReadMe.txt text file included in the VA download for additional information on deploying the VA using the various Hypervisors.
8 Note	The VA has 4 network adapters. For VMware only the first adapter (eth0) is connected by default. For HyperV, KVM, XEN and Nutanix AHV all adapters are disconnected by default. Use

the network configuration screen within the Hypervisor to connect the required adapters.

8.2. Initial Network Configuration

After boot up, follow the instructions on the appliance console to configure the management IP address, subnet mask, default gateway, DNS servers and other network and administrative settings.

(!) Important Be sure to set a secure password for the load balancer, when prompted during the setup routine.

8.3. Accessing the Appliance WebUI

The WebUI is accessed using a web browser. By default, users are authenticated using Apache authentication. Users can also be authenticated against LDAP, LDAPS, Active Directory or Radius - for more information, please refer to External Authentication.

Note There are certain differences when accessing the WebUI for the cloud appliances. For details, please refer to the relevant Quick Start / Configuration Guide.

1. Using a browser, navigate to the following URL:



https://<IP-address-configured-during-the-network-setup-wizard>:9443/lbadmin/

You'll receive a warning about the WebUI's SSL certificate. This is due to the default self signed certificate that is used. If preferred, you can upload your own certificate - for more information, please refer to Appliance Security Features.

Note

If you need to change the port, IP address or protocol that the WebUI listens on, please refer to Service Socket Addresses.

2. Log in to the WebUI using the following credentials:

Username: loadbalancer


Password: <configured-during-network-setup-wizard>

Note To change the password, use the WebUI menu option: *Maintenance > Passwords*.

Once logged in, the WebUI will be displayed as shown below:

LOADBALANCER





3. You'll be asked if you want to run the Setup Wizard which can be used to configure layer 7 services. Click **Dismiss** if you're following a guide or want to configure the appliance manually or click **Accept** to start the wizard.

Main Menu Options

System Overview - Displays a graphical summary of all VIPs, RIPs and key appliance statistics

Local Configuration - Configure local host settings such as IP address, DNS, system time etc.

Cluster Configuration - Configure load balanced services such as VIPs & RIPs

Maintenance - Perform maintenance tasks such as service restarts and taking backups

View Configuration - Display the saved appliance configuration settings

Reports - View various appliance reports & graphs

Logs - View various appliance logs

Support - Create a support download, contact the support team & access useful links

Live Chat - Start a live chat session with one of our Support Engineers



8.4. Appliance Software Update

To ensure that the appliance(s) are running the latest software version, we recommend a software update check is performed.

Determining the Current Software Version

The software version is displayed at the bottom of the WebUI as shown in the example below:

Copyright © Loadbalancer.org Inc. 2002 – 2024 ENTERPRISE VA Max - v8.11.1



Checking for Updates using Online Update

8 Note

By default, the appliance periodically contacts the Loadbalancer.org update server and checks for updates. An update check can also be manually triggered as detailed below.

- 1. Using the WebUI, navigate to: Maintenance > Software Update.
- 2. Select Online Update.
- 3. If the latest version is already installed, a message similar to the following will be displayed:

Information: Version v8.11.1 is the current release. No updates are available

- 4. If an update is available, you'll be presented with a list of new features, improvements, bug fixes and security related updates.
- 5. Click **Online Update** to start the update process.

8 Note

Do not navigate away whilst the update is ongoing, this may cause the update to fail.

6. Once complete (the update can take several minutes depending on download speed and upgrade version) the following message will be displayed:

Information: Update completed successfully.

7. If services need to be reloaded/restarted or the appliance needs a full restart, you'll be prompted accordingly.

Using Offline Update

If the load balancer does not have access to the Internet, offline update can be used.

8 Note

Please contact support@loadbalancer.org to check if an update is available and obtain the latest offline update files.

To perform an offline update:

- 1. Using the WebUI, navigate to: *Maintenance > Software Update*.
- 2. Select Offline Update.
- 3. The following screen will be displayed:

Software Update

Offline Update

The following steps will lead you through offline update.

- Contact Loadbalancer.org support to obtain the offline update archive and checksum.
- 2. Save the archive and checksum to your local machine.
- Select the archive and checksum files in the upload form below.
- 4. Click Upload and Install to begin the update process.



- 4. Select the Archive and Checksum files.
- 5. Click Upload and Install.
- 6. If services need to be reloaded/restarted or the appliance needs a full restart, you'll be prompted accordingly.

8.5. Ports Used by the Appliance

By default, the appliance uses the following TCP & UDP ports:

Protocol	Port	Purpose
TCP	22 *	SSH
TCP & UDP	53 *	DNS / GSLB
TCP & UDP	123	NTP
TCP & UDP	161 *	SNMP
UDP	6694	Heartbeat between Primary & Secondary appliances in HA mode
TCP	7778	HAProxy persistence table replication
TCP	9000 *	Gateway service (Centralized/Portal Management)
TCP	9080 *	WebUI - HTTP (disabled by default)
TCP	9081 *	Nginx fallback page

Protocol	Port	Purpose
TCP	9443 *	WebUI - HTTPS
TCP	25565 *	Shuttle service (Centralized/Portal Management)

The ports used for SSH, GSLB, SNMP, the WebUI, the fallback page, the gateway service and the shuttle service can be changed if required. For more information, please refer to Service Socket Addresses.


8.6. HA Clustered Pair Configuration

Loadbalancer.org recommend that load balancer appliances are deployed in pairs for high availability. In this guide a single unit is deployed first, adding a secondary unit is covered in the section Configuring HA - Adding a Secondary Appliance of the appendix.

9. Appliance Configuration for Nutanix Object Storage

9.1. Configuring VIP 1 - Nutanix-HTTP

- 1. Using the WebUI, navigate to *Cluster Configuration > Layer 7 Virtual Services* and click on **Add a new**Virtual Service.
- 2. Enter the following details:




- 3. Define the Label for the virtual service as required, e.g. Nutanix-HTTP.
- 4. Set the Virtual Service IP Address field to the required IP address, e.g. 192.168.110.100.
- 5. Set the *Ports* field to **80**.
- 6. Set the Layer 7 Protocol to TCP Mode.
- 7. Click **Update** to create the virtual service.
- 8. Now click **Modify** next to the newly created VIP.
- 9. Scroll to the Persistence section.

- Set the Persistence Mode to None.
- 10. Leave all other settings at their default value.
- 11. Click Update.

9.2. Defining the Real Servers (RIPs)


- 1. Using the WebUI, navigate to *Cluster Configuration > Layer 7 Real Servers* and click on **Add a new Real**Server next to the newly created VIP.
- 2. Enter the following details:



- 3. Define the *Label* for the real server as required, e.g. **NutanixObjectStorage-1**.
- 4. Set the Real Server IP Address field to the required IP address, e.g. 192.168.110.110.
- 5. Set the Real Server Port field to 80.
- 6. Leave all other settings at their default value.
- 7. Click **Update**.
- 8. Repeat these steps to add the remaining Nutanix Object Storage nodes.

9.3. Configuring VIP 2 - Nutanix-HTTPS


- 1. Using the WebUI, navigate to *Cluster Configuration > Layer 7 Virtual Services* and click on **Add a new**Virtual Service.
- 2. Enter the following details:



- 3. Define the *Label* for the virtual service as required, e.g. **Nutanix-HTTPS**.
- 4. Set the Virtual Service IP Address field to the required IP address, e.g. 192.168.110.100.
- 5. Set the Ports field to 443.
- 6. Set the Layer 7 Protocol to TCP Mode.
- 7. Click **Update** to create the virtual service.
- 8. Now click **Modify** next to the newly created VIP.
- 9. Scroll to the *Persistence* section.
 - Set the *Persistence Mode* to **None**.
- 10. Leave all other settings at their default value.
- 11. Click Update.

9.4. Defining the Real Servers (RIPs)

- 1. Using the WebUI, navigate to *Cluster Configuration > Layer 7 Real Servers* and click on **Add a new Real**Server next to the newly created VIP.
- 2. Enter the following details:



3. Define the *Label* for the real server as required, e.g. **NutanixObjectStorage-1**.

- 4. Set the Real Server IP Address field to the required IP address, e.g. 192.168.110.110.
- 5. Set the Real Server Port field to 443.
- 6. Leave all other settings at their default value.
- 7. Click **Update**.
- 8. Repeat these steps to add the remaining Nutanix Object Storage nodes.

9.5. Finalizing the Configuration

To apply the new settings, HAProxy must be reloaded. This can be done using the button in the "Commit changes" box at the top of the screen or by using the *Restart Services* menu option:

- 1. Using the WebUI, navigate to: *Maintenance > Restart Services*.
- 2. Click Reload HAProxy.

10. Testing & Verification

8 Note


For additional guidance on diagnosing and resolving any issues you may have, please also refer to Diagnostics & Troubleshooting.

10.1. Accessing Nutanix Object Storage

Verify that you can access Nutanix Object Storage by connecting to the VIP address on the load balancer rather than one of the storage nodes. If you connect using a FQDN, first modify DNS to point at the VIP address.

10.2. Using System Overview

The System Overview can be viewed in the WebUI. It shows a graphical view of all VIPs & RIPs (i.e. the Nutanix Object Storage nodes) and shows the state/health of each server as well as the state of the cluster as a whole. The example below shows that all three Nutanix Object Storage nodes are healthy and available to accept connections:



11. Technical Support

For more details about configuring the appliance and assistance with designing your deployment please don't hesitate to contact the support team using the following email address: support@loadbalancer.org.

12. Further Documentation

For additional information, please refer to the Administration Manual.

13. Appendix

13.1. Configuring HA - Adding a Secondary Appliance

Our recommended configuration is to use a clustered HA pair of load balancers to provide a highly available and resilient load balancing solution. We recommend that the Primary appliance is fully configured first, then the Secondary appliance can be added to create an HA pair. Once the HA pair is configured, load balanced services must be configured and modified on the Primary appliance. The Secondary appliance will be automatically kept in sync.

Note

For Enterprise Azure, the HA pair should be configured first. For more information, please refer to the Azure Quick Start/Configuration Guide available in the documentation library

The clustered HA pair uses Heartbeat to determine the state of the other appliance. Should the active device (normally the Primary) suffer a failure, the passive device (normally the Secondary) will take over.

Non-Replicated Settings

A number of settings are not replicated as part of the Primary/Secondary pairing process and therefore must be manually configured on the Secondary appliance. These are listed by WebUI menu option in the table below:

WebUI Main Menu Option	Sub Menu Option	Description
Local Configuration	Hostname & DNS	Hostname and DNS settings
Local Configuration	Network Interface Configuration	Interface IP addresses, bonding configuration and VLANs
Local Configuration	Routing	Default gateways and static routes
Local Configuration	System Date & time	Time and date related settings
Local Configuration	Physical – Advanced Configuration	Various appliance settings
Local Configuration	Portal Management	Portal management settings
Local Configuration	Security	Security settings
Local Configuration	SNMP Configuration	SNMP settings
Local Configuration	Graphing	Graphing settings
Local Configuration	License Key	Appliance licensing
Maintenance	Backup & Restore	Local XML backups
Maintenance	Software Updates	Appliance software updates
Maintenance	Fallback Page	Fallback page configuration
Maintenance	Firewall Script	Firewall (iptables) configuration
Maintenance	Firewall Lockdown Wizard	Appliance management lockdown settings

(!) Important

Make sure that where any of the above have been configured on the Primary appliance, they're also configured on the Secondary.


Configuring the HA Clustered Pair

8 Note

If you have already run the firewall lockdown wizard on either appliance, you'll need to ensure that it is temporarily disabled on both appliances whilst performing the pairing process.


- 1. Deploy a second appliance that will be the Secondary and configure initial network settings.
- 2. Using the WebUI on the Primary appliance, navigate to: *Cluster Configuration > High-Availability Configuration*.

Create a Clustered Pair



- 3. Specify the IP address and the *loadbalancer* user's password for the Secondary (peer) appliance as shown in the example above.
- 4. Click Add new node.
- 5. The pairing process now commences as shown below:

Create a Clustered Pair




6. Once complete, the following will be displayed on the Primary appliance:



High Availability Configuration - primary



7. To finalize the configuration, restart heartbeat and any other services as prompted in the "Commit changes" message box at the top of the screen.



14. Document Revision History

Version	Date	Change	Reason for Change	Changed By
1.0.0	25 January 2024	Initial version		DS, RJC





Visit us: www.loadbalancer.org

Phone us: +44 (0)330 380 1064

Phone us: +1 833 274 2566

Email us: info@loadbalancer.org

Follow us: @loadbalancer.org

About Loadbalancer.org

Loadbalancer.org's mission is to ensure that its clients' businesses are never interrupted. The load balancer experts ask the right questions to get to the heart of what matters, bringing a depth of understanding to each deployment. Experience enables Loadbalancer.org engineers to design less complex, unbreakable solutions and to provide exceptional personalized support.

